



EM-100 Emergency Button

This is a circular emergency button which adopts low power consumption wireless transmission chip. It has very good performance on penetration .

When there' s emergency incidents, press this button, and it will send alarm signal to alarm host to achieve remote alarm. Then alarm host will take picture or make record for incident area immediately. Related snapshots and videos information will be sent to client software or App, so guard people or user can deal with the emergency incidents in time.

Features



Wireless communication with Alarm Host



Anti High-frequency interference



Super low power consumption



Rolling code for anti-crack

Specifications

Model Name	EM-100 (Emergency Button)
Working Voltage	3V CR2032 button cell battery
Alarm Current	≤ 30mA
Standby Current	≤ 15uA
RF Distance	≥ 30M (open area)
Temperature	-10°C ~+50°C
Humidity	≤ 95%
Mounting Type	Wall Mounting
Alarm format	Remote alarm (mating alarm host)
Radio Frequency	915MHz/FSK
Measurement	60*13 mm

Attentions

Please check whether the Emergency Button is online or not or under low voltage through cellphone APP. Please check immediately if it' s offline or replace the battery if it' s under low voltage.

Ansee Co. Ltd

Add: Building A, GuanLong First Industry Park,
XiLi Town, NanShan District, Shenzhen, China
(518055)

Tel: 0755-86521099/86522966

Fax: 0755-26984949

Email: sales@anseetec.com

Web: www.anseetec.com